



powerbloc[™] FPT 6 Volt • 8 Volt • 12 Volt



The EnerSys[®] powerbloc[™] FPT line provides quality constructed flat plate batteries which are perfect replacements in existing equipment.

Cell Construction

The powerbloc[™] FPT range has advanced flat grid plates and paste formulation giving extended service life. It is especially suited to arduous deep cycle semi-traction applications.

Benefits

- Advanced separator design and paste formulation gives true 700 cycle performance.
- Enhanced performance gives extended running times and lower maintenance.
- Superior performance means more productive run-time.



Model Number	powerbloc™ 6 Volt Battery	C20 Amp-Hour Rate	C5 Amp-Hour Rate	Minutes @75 Amps	Minutes @25 Amps	Length (in)	Width (in)	Height (in)	Weight (lb)	# of Cycles
6FPT175	6 Volt Lead Acid Battery - (BCI Size GC2)	216	172	114	445	10.25	7.12	11.25	63	700
6FPT185	6 Volt Lead Acid Battery - (BCI Size GC2)	232	181	122	474	10.23	7.12	11.25	63	700
6FPT195	6 Volt Lead Acid Battery - (BCI Size GC2)	242	198	140	517	10.23	7.12	11.25	67	700
6FPT210	6 Volt Lead Acid Battery - (BCI Size GC2)	251	216	154	562	10.23	7.12	11.88	70	700
6FPT215	6 Volt Lead Acid Battery - (BCI Size 901)	255	217	159	570	11.63	7.12	11.61	72	700
6FPT255	6 Volt Lead Acid Battery - (BCI Size 902)	310	253	185	715	11.63	7.12	14.63	87	700
6FPT305	6 Volt Lead Acid Battery - (BCI Size 903)	380	296	225	855	11.63	7.12	16.75	110	700
Model Number	powerbloc™ 8 Volt Battery	C20 Amp-Hour Rate	C5 Amp-Hour Rate	Minutes @75 Amps	Minutes @25 Amps	Length (in)	Width (in)	Height (in)	Weight (lb)	# of Cycles
8FPT145	8 Volt Lead Acid Battery - (BCI Size GC8)	170	138	90	337	10.23	7.12	11.25	66	700
Model Number	powerbloc™ 12 Volt Battery	C20 Amp-Hour Rate	C5 Amp-Hour Rate	Minutes @75 Amps	Minutes @25 Amps	Length (in)	Width (in)	Height (in)	Weight (lb)	# of Cycles
12FPT85	12 Volt Lead Acid Battery - (BCI Size 27)	105	90	42	205	12.75	6.75	9.75	112	700
12FPT105	12 Volt Lead Acid Battery - (BCI Size 31)	130	99	49	225	13.00	6.75	9.75	122	700
12FPT120	12 Volt Lead Acid Battery - (BCI Size 920)	155	122	77	292	13.12	7.06	11.37	86	700
12FPT150	12 Volt Lead Acid Battery - (BCI Size 921)	200	158	106	398	15.62	7.06	14.87	109	700

FPT (ONLY) powerblocs™ terminated with (2) UTL and (1) OFF SET S.

Terminal Options



1 - off-set "S"



2 - UTL



3 - UT



4 - Large "L"



Automotive Post (AP)

EnerSys® also offers a complete line of battery chargers, for both on-board or off-board applications. Please see your local EnerSys representative for further details and information.



ENERSYS WORLD HEADQUARTERS
2366 Bernville Road
Reading, PA 19605
Phone: +1-800-EnerSys
Fax: +610-372-8613
www.enersys.com

ENERSYS CANADA INC.
61 Parr Boulevard Unit 3
Bolton, Ontario • Canada L7E 4E3
Phone: +1-800-363-4877
Fax: +1-905-951-4441

ENERSYS DE MEXICO SA DE CV
Ave Lopez Mateos #4210
Colonia Casa Blanca • C.P. 66475
San Nicolas de los Garza, N.L. Mexico
Phone: +52-818-329-6400
Fax: +52-818-329-6489